

Pot Cores (5698362321)



Part Number: 5698362321

98 POT CORE SET

Pot cores have found application in all types of inductive devices. The core configuration provides a high degree of self-shielding. It also facilitates gapping to enhance utility for a variety of magnetic designs.

 \Box Pot cores can be supplied with the center post gapped to a mechanical dimension or an A_L value.

Weight indicated is per pair or set.

Weight: 54.000 (g)

A 35.6 B 10.9 C 26.2 D 7.6 E 29.5 F 15.9	mm tol ±0.60 ±0.20 ±0.60 ±0.30 min	nominal inch 1.402 0.429 1.031 0.299 1.161	inch misc.	Chart Legend Σl/ A : Core Constant, l _a : Effective Path
B 10.9 C 26.2 D 7.6 E 29.5 F 15.9	±0.20 ±0.60 ±0.30	0.429 1.031 0.299		
D 7.6 E 29.5 F 15.9	±0.30	0.299		
E 29.5 F 15.9				
F 15.9	min	1 161		— ZI/ A · CORE CONSIANT I · ETTECTIVE PAIN
		1.101	mın	Length, A.: Effective Cross- Sectional Area, Effective Core Volume
	±0.30	0.626	_	
G 5.15	±0.40	0.203	_	
H 5.45	±0.25	0.215		A _L : Inductance Factor

Electrical Properties				
$A_L(nH)$	8500 ±25%			
Ae(cm ²)	1.84			
$\Sigma l/A(cm^{-1})$	2.9			
l _e (cm)	5.53			
$V_e(cm^3)$	9.78			
$A_{min}(cm^2)$	1.64			

A, value is measured at 1 kHz, B < 10 gauss.

Fair- Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288

888-324-7748

845-895-2055

Fax: 845-895-2629

ferrites@fair- rite.com

www.fair- rite.com